

This KX amplifier delivers as much as 100 watts per channel (4 channels driven), or 200 watts into two sets of bridged channels. See below for more details.

## Specifications

### **RMS Power [Watts]**

---

@ 14.4V, 4 $\Omega$  stereo,  $\leq$  1% THD+N: 50 x 4

@ 14.4V, 2 $\Omega$  stereo,  $\leq$  1% THD+N: 100 x 4

@ 14.4V, 4 $\Omega$  bridged mono,  $\leq$  1% THD+N: 200 x 2

### **Length [in, cm]**

---

11-<sup>3</sup>/<sub>16</sub>, 28.4

### **Height [in, cm]**

---

2-<sup>1</sup>/<sub>8</sub>, 5.5

### **Width [in, cm]**

---

8-<sup>5</sup>/<sub>16</sub>, 21

### **Frequency Response [Hz]**

---

10Hz–20kHz

### **Input Sensitivity:**

---

250mV–10V

### **Signal-to-Noise Ratio**

---

95dB

### **Selectable Electronic Crossover**

---

Amp 1: OFF/HP/LP; Variable 10–5,000Hz with X10 switch

Amp 2: OFF/HP/LP/BP; Variable HP, 10–500Hz;

Variable LP, 40–5,000Hz with 10X switch

Slope: 24dB/octave

### **KickEQ™ Bass Boost**

---

0–18dB @ 40Hz

### **CEA Power**

---

50 x 4 @ 4 ohms, 14.4VDC, 1% THD, CEA-2006B (Watts)

### **CEA Signal-to-Noise Ratio**

---

-75dB CEA-2006B (ref: 1W, A-weighted)

## Support