

# HD-MD-200-C-1G-E Series

## DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200 w/Wall Plate Transmitter

- > 1+1 high-definition digital AV switcher, scaler, and extender
- > Fully-automatic operation — no control system, control panel, or programming required!
- > Easy web browser setup
- > Supports integration with a Crestron® control system for fully programmable functionality
- > Includes a wall plate transmitter and surface-mountable receiver
- > Transmitter includes a single HDMI® input<sup>[2]</sup>
- > Compatible with the Crestron Multihead HD Video Cable (CBL-MULTI-HD-6, sold separately)
- > USB power port supplies power for the Multihead cable and other USB powered devices<sup>[5]</sup>
- > Receiver includes one HDMI input, one HDMI output, and one analog audio output<sup>[2,3,4]</sup>
- > A single CATx cable links the transmitter to the receiver<sup>[1]</sup>
- > Supports cable lengths up to 230 feet (70 meters) between the transmitter and receiver<sup>[1]</sup>
- > Automatically scales input signals to match the native resolution of the room display
- > Supports a range of display resolutions up to Full HD 1080p and WUXGA
- > Supports any input resolution up to Full HD 1080p and WUXGA<sup>[7]</sup>
- > Performs deinterlacing of NTSC, PAL, and 1080i sources
- > Handles Dolby Digital® 5.1, DTS® 5.1, and uncompressed 7.1 linear PCM audio
- > Supports stereo audio de-embedding via the analog audio output<sup>[4]</sup>
- > Provides up to 150 ms lip-sync delay at the analog output
- > QuickSwitch HD™ technology manages HDCP keys for fast, reliable switching
- > Includes comprehensive built-in EDID configuration tools
- > Provides a 10/100 Ethernet LAN connection
- > Enables device control via CEC, IR, or RS-232
- > Universal 100-240V external power pack included
- > Decorator style faceplate sold separately

The Crestron® **HD-MD-200-C-1G-E** delivers an incredibly simple and cost-effective multimedia presentation solution for classrooms and meeting spaces. It allows a laptop or mobile device to be connected at a wall plate via HDMI®, and routes the signal to a display or projector up to 230 feet (70 meters) away. An additional HDMI source can be connected at the display device location (or through an optional wall plate near the display). Fully automatic operation detects when a source is connected or disconnected at either input and turns the display on and off, alleviating the need for any control panels or remotes. Built-in scaling ensures an optimal video image for SD and HD video signals, as well as for high-res computer signals.

Composed of a compact transmitter and receiver pair (models **HD-TX-101-C-1G-E** and **HD-RX-201-C-E** respectively), the HD-MD-200-C-1G-E installs in minutes and requires no special programming. The transmitter mounts in a standard one-gang US electrical box, while the receiver mounts behind the display or above the projector. The only connection required between



the transmitter and receiver is a single CAT type twisted pair cable.<sup>[1]</sup> A LAN port on the receiver allows for connection to an Ethernet network to enable easy setup and configuration via a web browser. Advanced functionality is enabled through integration with a Crestron control system.

### Computer/AV Auto-Switcher

The HD-MD-200-C-1G-E handles high-definition video and computer sources with resolutions up to Full HD 1080p60, 1080i30, or WUXGA 1920x1200. A single HDMI input is provided on the transmitter to support the connection of a computer, mobile device, or other media source. An additional HDMI input is provided on the receiver, which may be wired to an optional [wall plate](#) or used to connect a local source such as a mini PC or Crestron [AirMedia®](#) wireless presentation system.

The inputs on both components can be configured to switch automatically or be controlled through a Crestron control system. Auto-detection on each input enables plug-and-play simplicity, supporting HDMI, DVI, or Dual-Mode DisplayPort signals via either HDMI input.<sup>[2]</sup> The auto-switching behavior can be configured using “priority routing” mode, allowing the installer to define which input takes precedence over the other when connecting multiple sources.

A single HDMI output is provided on the receiver to feed the display device. This output can support either HDMI or DVI signal types.<sup>[3]</sup> A stereo analog audio output is also included to feed an optional [sound bar](#) or [amplifier](#).<sup>[4]</sup>

### Multihead Cable Option

A USB power port is included on the HD-TX-101-C-1G-E transmitter to enable use of a Crestron Multihead HD Video Cable (model [CBL-MULTI-HD-6](#), sold separately). The Multihead cable provides expanded input connectivity to support the connection of a laptop computer or mobile device with HDMI, DisplayPort, Mini DisplayPort, or USB Type-C™ video output.<sup>[5]</sup>

# HD-MD-200-C-1G-E DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200

## HD Signal Extender

A single CAT type cable (sold separately) links the HD-MD-200-C-1G-E transmitter and receiver together. This cable can be up to 230 feet (70 meters) in length, offering an ideal point-to-point signal extender solution for virtually any room with a single display device.<sup>[1]</sup>

## HD Scaler

One might assume that any modern display device should support whatever sources you connect to it. In fact, many displays just can't handle all the different formats and resolutions you're likely to encounter day-to-day in a dynamic presentation environment. With its built-in professional scaler, the HD-MD-200-C-1G-E enables support for a complete range of digital and analog signals, ensuring that every source displays reliably and beautifully. Automatic calibration is achieved using the display's EDID<sup>[6]</sup> — just connect the receiver to the display and it intelligently converts and enhances the signal for optimal appearance on the display screen.

## EDID Format Management

To ensure that every source gets displayed at its optimal resolution and format, the HD-MD-200-C-1G-E provides comprehensive management of the EDID information that passes between the display, scaler, and source devices. Most applications require no changes to the default settings. For applications requiring custom configuration, the HD-MD-200-C-1G-E allows for easy assessment of each device's format and resolution capabilities, with the ability to configure signals appropriately for the most desirable and predictable behavior.

## QuickSwitch HD™ Technology

Handling digital media signals means handling HDCP (High-bandwidth Digital Content Protection), the encryption scheme used by content providers to protect their DVDs, Blu-ray™ discs, and broadcast signals against unauthorized copying. Viewing HDCP encrypted content requires a source device to “authenticate” each display and signal processor in the system and issue it a “key” before delivering an output signal. Crestron QuickSwitch HD manages these keys to ensure fast, reliable switching and immunity to “blackouts.”

## Audio De-Embedding

Its analog audio output allows the HD-MD-200-C-1G-E to extract the stereo audio signal from digital sources to feed a sound bar, amplified speakers, or a separate sound system.<sup>[4]</sup>

## Embedded Device Control

To deliver fully automatic operation of the complete system, the HD-MD-200-C-1G-E can turn the display device on and off via its HDMI connection using CEC (Consumer Electronics Control) commands, or via the built-in IR or RS-232 port. For advanced applications using a Crestron control system, all of the HDMI, IR, and RS-232 ports on the HD-MD-200-C-1G-E can be utilized to attain fully-programmable control of the display, sources, and other devices in the room.

## Control System Integration

Fully programmable functionality can be enabled through integration with a Crestron control system. Integration with a control system also enables centralized monitoring using the [Crestron Fusion®](#) Enterprise Management Service.



HD-MD-200-C-1G-E Transmitter (HD-TX-101-C-1G-E) – Front View  
White version shown with no faceplate



HD-MD-200-C-1G-E Receiver (HD-RX-201-C-E) – Rear, Top, and Front Views

## Low-Profile Installation

The wall plate transmitter (HD-TX-101-C-1G-E) is designed to mount in a single-gang US electrical box, while the receiver (HD-RX-201-C-E) typically mounts on the wall behind a flat-panel display or on the ceiling above a projector. Alternately, the receiver can be attached to a single rack rail in the back of an equipment cabinet. Both components are powered together using a single wall mount power pack (included) connected at the receiver location. Power is carried between the receiver and transmitter over the DM Lite link connection.

*Note: The HD-TX-101-C-1G-E requires a single-gang decorator style faceplate, Crestron FP-G1 Series or equivalent.*

# HD-MD-200-C-1G-E DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200

## Easy Setup

Simplified setup, configuration, and basic operation is provided through a Web browser user interface. Essential controls and status indicators are also provided on each unit for easy testing and troubleshooting without a computer during installation.

## SPECIFICATIONS

### Video

**Switcher:** 1+1 (1 input at transmitter + 1 input at receiver) manual or auto-switching, audio-follow-video, Crestron QuickSwitch HD technology

**Scaler:** HD video scaler and deinterlacer, noise reduction, 3:2/2:2 pull-down detection and recovery, aspect ratio selection, picture and RGB color adjustments

**Input Signal Types:** HDMI w/Deep Color (DVI & Dual-Mode DisplayPort compatible<sup>[2]</sup>)

**Output Signal Types:** HDMI w/Deep Color (DVI compatible<sup>[3]</sup>)

**Copy Protection:** HDCP 1.4

### Maximum Input Resolutions:

Input Type	Scan Type	Resolution	Frame Rate
HDMI	Progressive	1920x1200 WUXGA	60 Hz
		1920x1080 HD 1080p	60 Hz
	Interlaced	1920x1080 HD 1080i	30 Hz

*NOTE: Common resolutions are shown; other custom resolutions are supported at pixel clock rates up to 165 MHz*

**Scaler Output Resolutions, HDMI, Progressive:** Auto, 640x480@60Hz, 720x480@60Hz (480p), 720x576@50Hz (576p), 800x600@60Hz, 840x480@60Hz, 1024x768@60Hz, 1280x720@50/60Hz (720p50/60), 1280x768@60Hz<sup>[8]</sup>, 1280x800@60Hz<sup>[8]</sup>, 1280x960@60Hz, 1280x1024@60Hz, 1360x768@60Hz, 1366x768@60Hz<sup>[8]</sup>, 1400x1050@60Hz<sup>[8]</sup>, 1440x900@60Hz<sup>[8]</sup>, 1600x900@60Hz<sup>[9]</sup>, 1600x1200@60Hz, 1680x1050@60Hz<sup>[8]</sup>, 1920x1080@30/50/60Hz (1080p30/50/60), 1920x1200@60Hz<sup>[9]</sup>

**Scaler Output Resolutions, HDMI, Interlaced:** Auto, 480i, 576i, 1080i25, 1080i30

### Audio

**Input Signal Types:** HDMI (Dual-Mode DisplayPort compatible<sup>[2]</sup>)

**Output Signal Types:** HDMI, analog stereo<sup>[3]</sup>

**Digital Formats:** Dolby Digital, Dolby Digital EX, DTS, DTS ES, DTS 96/24, LPCM up to 8 channels

**Analog Formats:** Stereo 2-channel<sup>[4]</sup>

**Digital-To-Analog Conversion:** 24-bit 48 kHz

**Analog Output Volume:** -80 to +20 dB Level adjustment range, plus Mute

**Analog Output Lip-Sync Delay:** 0 to 150 ms (maximum delay time is reduced for input signals with sampling rates over 48 kHz)

### Analog Performance:

Frequency Response: 20 Hz to 20 kHz ±0.5 dB;

S/N Ratio: >95 dB, 20 Hz to 20 kHz A-weighted;

THD+N: <0.005% @ 1 kHz;

Stereo Separation: >80 dB

### Communications

**Ethernet:** 10/100 Mbps, auto-switching, auto-negotiating, auto-discovery, full/half duplex, DHCP, Web browser setup and control, Crestron control system integration

**RS-232:** 2-way device control and monitoring up to 115.2k baud with hardware and software handshaking

**IR:** 1-way device control via infrared up to 60 kHz

**HDMI:** HDCP 1.4, EDID, CEC

**DM Lite Link:** Proprietary link for connection between TX & RX only

*NOTE: Supports management of HDCP and EDID; supports management of CEC between the connected HDMI devices and a control system*

### Connectors at Transmitter (HD-TX-101-C-1G-E)

**HDMI IN:** (1) HDMI Type A connector, female;

HDMI digital video/audio input (DVI & Dual-Mode DisplayPort compatible<sup>[2]</sup>)

**POWER ONLY:** (1) USB Type A connector, female;

USB power port (500 mA maximum output);

Supplies power for a Crestron Multihead HD Video Cable

(**CBL-MULTI-HD-6**, sold separately) or other USB powered device

**TO RX (Rear):** (1) 8-pin RJ45 connector, female, shielded;

Link port for connection to HD-RX-201-C-E receiver<sup>[1]</sup>

**24VDC 1.25A (Rear):** (1) 2-pin 3.5 mm detachable terminal block; Not used

### Connectors at Receiver (HD-RX-201-C-E)

**HDMI, INPUT 1:** (1) HDMI Type A connector, female;

HDMI digital video/audio input (DVI & Dual-Mode DisplayPort compatible<sup>[2]</sup>)

**FROM TX, INPUT 2:** (1) 8-pin RJ45 connector, female, shielded;

Link port for connection to HD-TX-101-C-1G-E transmitter<sup>[1]</sup>;

Maximum cable length: 230 ft (70 m)

**HDMI OUTPUT:** (1) HDMI Type A connector, female;

HDMI digital video/audio output (DVI compatible<sup>[3]</sup>)

**AUDIO L/R:** (1) 5-pin 3.5mm detachable terminal block;

Balanced/unbalanced stereo line-level audio output<sup>[4]</sup>;

Maximum Output Level: 4 Vrms balanced, 2 Vrms unbalanced

Output Impedance: 200 Ohms balanced, 100 Ohms unbalanced

**IR:** (1) 2-pin 3.5 mm detachable terminal block;

IR output control port; Supports IR up to 60 kHz;

**IRP2** emitter sold separately;

*Note: Provides power on/off control of the display device without a control system, or fully programmable control of any device with a control system*

**COM:** (1) 5-pin 3.5 mm detachable terminal block;

Bidirectional RS-232 port; Supports RS-232 up to 115.2k baud with hardware and software handshaking;

*Note: Provides power on/off control of the display device without a control system, or fully programmable control of any device with a control system*

**LAN:** (1) 8-pin RJ45 connector, female;

10Base-T/100Base-TX Ethernet port



# HD-MD-200-C-1G-E DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200

**24VDC 1.25A:** (1) 2.1 x 5.5 mm DC power connector;  
24 Volt DC power input;  
**PW-2412WU** power pack included;

*Note: This connection powers both the receiver and transmitter*

**SERVICE:** (1) USB Type A connector, female;  
For factory use only

## Indicators at Transmitter (HD-TX-101-C-1G-E)

**PWR:** (1) Green LED, indicates operating power is supplied from the RX via the DM Lite link

**HDMI IN:** (1) Green LED, indicates HDMI input signal presence

**TO RX (Rear):** (2) LEDs (on RJ45 connector), green LED indicates DM Lite link status, amber LED indicates a valid video signal

## Controls & Indicators at Receiver (HD-RX-201-C-E)

**FROM TX, INPUT 2:** (2) LEDs (on RJ45 connector), green LED indicates DM Lite link status, amber LED indicates a valid video signal

**LAN:** (2) LEDs (on RJ45 connector), green LED indicates Ethernet link status, amber LED indicates Ethernet activity

**PWR:** (1) Bi-color green/amber LED, indicates operating power is supplied from the power pack via the 24VDC input, turns amber while booting and green when operating

**AUTO:** (1) Pushbutton to enable/disable auto-switching mode, and (1) green LED to indicate auto-switching mode is enabled

**INPUT 1 – 2:** (2) Pushbuttons for manual input selection, and (2) bi-color green/amber LEDs to indicate the current active input and signal presence at each corresponding input

**SETUP:** (1) Red LED and (1) recessed pushbutton for Ethernet setup

## Power

### Power Pack (included):

Input: 0.8 Amps (maximum) @ 100-240 Volts AC, 50/60 Hz;

Output: 1.25 Amps @ 24 Volts DC;

Model: **PW-2412WU**

*Note: The receiver and transmitter are powered together using a single power pack connected at the receiver.*

## Environmental

**Temperature:** 32° to 104°F (0° to 40°C)

**Humidity:** 20% to 90% RH (non-condensing)

## Construction

### Transmitter (HD-TX-101-C-1G-E):

**Composition:** Metal housing and bracket with black or white polycarbonate front label overlay;

**Mounting:** Mounts in a 1-gang, 2-1/4 inch (57 mm) deep U.S. electrical box or plaster ring (not included);

**Faceplate:** Requires a decorator-style faceplate (**FP-G series**, sold separately)

### Receiver (HD-RX-201-C-E):

**Chassis:** Metal, black finish, with (2) integral mounting flanges, vented sides;

**Mounting:** Freestanding, surface mount, or attach to a single rack rail

## Dimensions

**Transmitter (HD-TX-101-C-1G-E):** Height: 4.08 in (104 mm);  
Width: 1.81 in (46 mm);  
Depth: 1.97 in (50 mm)

**Receiver (HD-RX-201-C-E):** Height: 1.11 in (28 mm);  
Width: 7.70 in (196 mm);  
Depth: 4.94 in (126 mm)

## Weight

**Transmitter (HD-TX-101-C-1G-E):** 5.30 oz (150 g)

**Receiver (HD-RX-201-C-E):** 20.82 oz (590 g)

## Compliance

UL Listed for US & Canada, CE, IC, FCC Part 15 Class B digital device

## MODELS & ACCESSORIES

### Available Models

**HD-MD-200-C-1G-E-B:** DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200 w/Wall Plate Transmitter, Black

**HD-MD-200-C-1G-E-W:** DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200 w/Wall Plate Transmitter, White

### Included Accessories

**HD-TX-101-C-1G-E-B-T:** DM Lite – HDMI® over CATx Transmitter, Wall Plate, Black Textured (Qty. 1 included with HD-MD-200-C-1G-E-B only)

**HD-TX-101-C-1G-E-W-T:** DM Lite – HDMI® over CATx Transmitter, Wall Plate, White Textured (Qty. 1 included with HD-MD-200-C-1G-E-W only)

**HD-RX-201-C-E:** DM Lite – HDMI® over CATx Receiver, Room Controller, 2x1 Auto-Switcher, HD Scaler, Surface Mount (Qty. 1 included)

**PW-2412WU:** Wall Mount Power Pack, 24VDC, 1.25A, 2.1mm, Universal (Qty. 1 included)

### Available Accessories

**FP-G1 Series:** 1-Gang Decorator Style Faceplates

**DM-CBL-8G-NP Series:** DigitalMedia 8G™ Cable, non-plenum

**DM-CBL-8G-P Series:** DigitalMedia 8G™ Cable, plenum

**DM-8G-CONN-WG-100:** Connectors with Wire Guide for DM-CBL-8G DigitalMedia 8G™ Cable, 100-Pack

**DM-8G-CRIMP-WG:** Crimping Tool for DM-8G-CONN-WG

**CBL Series:** Crestron® Certified Interface Cables

**CBL-MULTI-HD-6:** Crestron Mercury® Multihead HD Video Cable, 6 ft (1.8 m)

**MP-WP Series:** Media Presentation Wall Plates

**CNSP-XX:** Custom Serial Interface Cable

**IRP2:** IR Emitter w/Terminal Block Connector

# HD-MD-200-C-1G-E DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200

**AM-200:** AirMedia® Presentation System 200

**SAROS SB-200-P-B:** Saros® Sound Bar 200, Powered

**MP-AMP30:** Media Presentation Audio Amplifier

**AMP Series:** Modular Power Amplifiers

## Notes:

1. For the DM Lite link cable between the TX and RX, use Crestron [DM-CBL-8G](#) DigitalMedia 8G™ cable or third-party CAT5e (or better). The maximum cable length is 230 ft (70 m). Shielded cable and connectors are required when bundling multiple cables in a wire run, and are recommended for all applications to safeguard against unpredictable environmental electrical noise which may impact performance at resolutions above 1080p. All wire and cables are sold separately. DM Lite devices are not compatible with DigitalMedia 8G+® (DM 8G+®), HDBaseT®, PoE, PoDM, or any other CATx based interface or network.
2. Each HDMI input requires an appropriate adapter or interface cable to accommodate a DVI or Dual-Mode DisplayPort signal. [CBL-HD-DVI](#) interface cables are available separately.
3. The HDMI output requires an appropriate adapter or interface cable to accommodate a DVI signal. [CBL-HD-DVI](#) interface cables are available separately.
4. The analog stereo audio output is only active when the input is receiving a 2-channel stereo signal.
5. The USB power port on the transmitter supplies power only (500 mA maximum) and is suitable for general use to power USB powered devices. No USB data is passed through this connection. It cannot be used to extend USB data, video, or audio signals.
6. EDID (Extended Display Identification Data) is data embedded in an HDMI, DVI, or VGA signal that enables the display device to tell the scaler what resolutions and formats it can support, allowing the scaler to configure itself automatically to feed an optimal output signal to the display.
7. Supports any input resolution and scan rate that has a pixel clock of 165 MHz or lower.
8. With or without reduced blanking.
9. With reduced blanking only.

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at <https://www.crestron.com/How-To-Buy/Find-a-Representative> or by calling 855-263-8754.

The specific patents that cover this and other Crestron products are listed online at <https://www.crestron.com/legal/patents>.

Certain Crestron products contain open source software. For specific information, visit <https://www.crestron.com/opensource>.

Crestron, the Crestron logo, AirMedia, Crestron Fusion, Crestron Mercury, DigitalMedia 8G, DigitalMedia 8G+, DM 8G+, QuickSwitch HD, and Saros are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Blu-ray is either a trademark or registered trademark of the Blu-ray Disc Association in the United States and/or other countries. Dolby Digital is either a trademark or registered trademark of Dolby Laboratories in the United States and/or other countries. DTS is either a trademark or registered trademark of DTS, Inc. in the United States and/or other countries. HDBaseT is either a trademark or registered trademark of the HDBaseT Alliance in the United States and/or other countries. HDMI and the HDMI Logo are either trademarks or registered trademarks of HDMI Licensing LLC in the United States and/or other countries. USB Type-C is either a trademark or registered trademark of USB Implementers Forum, Inc. in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography. Specifications are subject to change without notice.  
©2018 Crestron Electronics, Inc.

# HD-MD-200-C-1G-E

DM Lite – HD Scaling Auto-Switcher & HDMI® over CATx Extender 200

