

This KX amplifier delivers as much as 200 watts per channel (stereo) or 400 watts into one channel (mono). See below for more details.

Specifications

RMS Power [Watts]

@ 14.4V, 4 Ω stereo, \leq 1% THD+N : 100 x 2
@ 14.4V, 2 Ω stereo, \leq 1% THD+N : 200 x 2
@ 14.4V, 4 Ω bridged mono, \leq 1% THD+N: 400 x 1

Length [in, cm]

9- $\frac{9}{16}$, 24.4

Height [in, cm]

2- $\frac{1}{8}$, 5.5

Width [in, cm]

8- $\frac{5}{16}$, 21

Frequency Response \pm 1dB

10Hz–20kHz

Signal-to-Noise Ratio [dB]

95

Input Sensitivity

250mV-10V

Selectable Electronic Crossover

Off

Variable HP, 10-500Hz

Variable LP, 40-500Hz; 400Hz–5,000Hz with 10X Switch (BP capable)

Slope: 24dB/octave

KickEQ+™ Bass Boost

0-18dB @ 40Hz

CEA Power

100 x 2 @ 4 ohms, 14.4VDC, 1% THD, CEA-2006B (Watts)

CEA Signal-to-Noise Ratio

-75dB CEA-2006B (ref: 1W, A-weighted)