



FEATURES & BENEFITS

- + 5 Elements** - The cooktop's total output power is 9,300W. Comes with one 11-inch cooking zone with 3,700W power boost mode, two 9-inch cooking zone with 2,100W boost mode and two 7-inch cooking zone with 1,500W boost mode to cover your cooking needs.
- + 9 Power Levels** - So you can simmer a sauce or crank up the heat for a caramelized sear—now that's control
- + Power Boost** - The cooktop elements offer a power boost adjustment so you get to your desired temperature fast
- + Touch Controls** - Digital LED displays are touch and slide controlled and easy-to-read for the whole family and spills and grease can easily wipe away
- + Residual Heat Indicators and Lock** - This cooktop also features a Residual Heat Indicator and Child Lock so that you and your kiddos don't burn your hands
- + Automatic Safety Shut-Off** - The unit will auto turn-off without a cooking pot present after 2-8 hours of non-operation-safety first. depending on power level. See the graph below for power levels and time.

FEATURES

99 min timer / Child Lock / 5 Booster / Keep Warm / Pause Function
9 level power setting
Individual residual heat indicator
2-8 hours - automatic safety switch off
Slide touch

TECHNICAL DETAILS

1. Induction (Heating element)
2. Power cord: 47 1/4" without plug
3. Voltage / Frequency: 240v /60Hz
4. Certification: ETL, RoHS, FCC
5. Amperage: 38.75A

PRODUCT DIMENSIONS

1. Product Size (inch) (W*D*H): 36" - 21" - 2 1/4"
2. Cut out Size (inch) (W*D): 33 7/8" - 9 5/16"
3. Carton Size (inch) (W*D*H): 40 3/8" - 27" - 6 7/8"
4. Product Net/Gross weight (lbs): 28.66 / 36.38

Power Level	LV. 1-3	LV. 4-6	LV. 7-9
Shut Off	8 hours	4 hours	2 hours

ELEMENT PERFORMANCE

Number of Elements	5
1. Left Rear zone: 7"	1200/1500W
2. Left Front zone: 9"	1800/2100W
3. Right Rear zone: 9"	1800/2100W
4. Right Front zone: 7"	1200/1500W
5. Central zone: 11"	2300/3700W
Total	9300W

WARRANTY: 2 YEARS ON PARTS AND LABOR

