

PROJECTION SYSTEM

Display Type	DLP
Native Resolution	FHD (1920 x 1080)**
Upscaling / Super Resolution	Yes
Projection size (Screen Size)	60" ~ 120"
Projection Image	60"@5.2 ft ,100"@8.7 ft
Aspect Ratio	16:9/Original/4:3/Vertical Zoom / 4-Way Zoom
Optical Zoom	Fixed
Focus	Manual
Throw Ratio	1.195
Projection Offset	100%
Brightness	Up to 1000 ANSI Lumens*
Contrast Ratio	150,000:1
Light Source	4CH LED
Light Source Life	Up to 30,000 hrs
Noise (Eco / Nrmal / High brightness)	24 / 26 / 29dB(A)
HDCP	HDCP2.2
HDR	HDR10

LG SMART TV

Premium content providers	Amazon Prime Video,Disney+,YouTube,Apple TV,SHOWTIME,STARZ,Redbox,AMC Theatres On Demand,Funimation***
App Store	Yes
Web Browser	Yes

CONNECTIVITY/WIRELESS

Bluetooth (with Speaker)	Yes
Screen Share (Wireless Mirroring with Mira Cast supporting Android/Window device)	Yes
Contents Sharing (with DLNA supporting device only	Yes
Apple Airplay2	Yes

AUDIO

Bluetooth® Sound Out	Yes
Built-in Speakers	6W (3W+3W Stereo)
Bluetooth AV Sync Adjustment	Yes
Dolby Atmos compatible	Yes

INPUTS/OUTPUTS

Audio out	1 (3.5mm), S/PDIF 1(Optical)
-----------	------------------------------

HDMI™	2
USB Type A	2 (USB2.0)
RJ45	1
HID (Keyboard/Mouse/GamePad Connection Thru USB)	Yes

POWER

Power Supply (Voltage/Hz)	Adapter 110W (100V – 240V @ 50~60 Hz)
Power Consumption	100W
Standby Mode	<0.5W

ACCESSORIES/MANUAL

Remote Control	1 Standard
Manual	Simple Book
Warranty Card	Yes
Adaptor	Yes
Power Cord	Yes

DIMENSIONS/WEIGHT

Product (WxHxD)	8.9" x 7.6" x 2.7"
Shipping Dimensions (WxHxD)	13" x 9.5" x 5.2"
Weight	3.7 lbs

Shipping Weight	6.2 lbs
-----------------	---------

WARRANTY/UPC

Limited Warranty	1 Year Parts and Labor
------------------	------------------------

UPC	195174018071
-----	--------------

*	
*	The brightness is based on the perceived brightness equivalent to the brightness of lamp projector
**	Full HD resolution with 2.1 million discrete pixels projected by XPR (Expanded Pixel Resolution) video processing
***	Some apps may be available via software update, which requiries internet connection.